

Standard-Configuration PX50 ModuScale Upgrade

PowerboxType PX50ms/upgrade	Description Power, Minutes	Battery	Partlist	Dimension (WxHxD) in mm	Weight in Kg
20KVA					
PX50ms/u/20/0	20 KVA, 0 Min	—	PX50ms/u/20/0	550x1800x750	175
PX50ms/u/20/21	20 KVA, 21 Min	40x24 Ah	PX50ms/u/20/0 + BX50ms/u/A	(580+550)x1800x750	725
PX50ms/u/20+20/0	(20 + 20) KVA, 0 Min	—	PX50ms/u/20+20/0	550x1800x750	225
PX50ms/u/20+20/21+21	(20 + 20) KVA, 21 Min	(2 x 40) x 24 Ah	PX50ms/u/20+20/0 + BX50ms/u/B	(580+550)x1800x750	1135
PX50ms/u/20+20+20/0	(20 + 20+20) KVA, 0 Min	—	PX50ms/u/20+20+20/0	550x1800x750	275
PX50ms/u/20+20+20/21+21+21	(20 + 20+20) KVA, 21 Min	(3x40)x24Ah	PX50ms/u/20+20+20/0 + BX50ms/u/C	(580+550)x1800x750	1545
30KVA					
PX50ms/u/30/0	30 KVA, 0 Min	—	PX50ms/u/30/0	550x1800x750	180
PX50ms/u/30/13	30 KVA, 13 Min	40x24 Ah	PX50ms/u/30/0 + BX50ms/u/A	(580+550)x1800x750	730
PX50ms/u/30+30/0	(30 + 30) KVA, 0 Min	—	PX50ms/u/30+30/0	550x1800x750	235
PX50ms/u/30+30/13+13	(30 + 30) KVA, 13 Min	(2 x 40) x 24 Ah	PX50ms/u/30+30/0 + BX50ms/u/B	(580+550)x1800x750	1145
PX50ms/u/30+30/31+31	(30 + 30) KVA, 31 Min	2x(2x40)x24Ah	PX50ms/u/30+30/0 + 2 x BX50ms/u/B	(2 x 580+550)x1800x750	2055
PX50ms/u/30+30+30/0	(30 + 30+30) KVA, 0 Min	—	PX50ms/u/30+30+30/0	550x1800x750	290
PX50ms/u/30+30+30/13+13+13	(30 + 30 +30) KVA, 13 Min	(3 x 40) x 24 Ah	PX50ms/u/30+30+30/0 + BX50ms/u/C	(580+550)x1800x750	1560
PX50ms/u/30+30+30/31+31+31	(30 + 30+30) KVA, 31 Min	2x(3x40)x24Ah	PX50ms/u/30+30+30/0 + 2 x BX50ms/u/C	(2x 580+550)x1800x750	2830
40KVA					
PX50ms/u/40/0	40 KVA, 0 Min	—	PX50ms/u/40/0	550x1800x750	190
PX50ms/u/40/12	40 KVA, 12 Min	(1x50)x24Ah	PX50ms/u/40/0 + BX50ms/u/5a	(580+550)x1800x750	830
PX50ms/u/40+40/0	(40 + 40) KVA, 0 Min	—	PX50ms/u/40+40/0	550x1800x750	248
PX50ms/u/40+40/12+12	(40 + 40) KVA, 12 Min	(2 x 50) x 24 Ah	PX50ms/u/40+40/0 + BX50ms/u/5b	(580+550)x1800x750	1390
PX50ms/u/40+40+40/0	(40 + 40+40) KVA, 0 Min	—	PX50ms/u/40+40+40/0	550x1800x750	306
PX50ms/u/40+40+40/12+12+12	(40+ 40+40) KVA, 12 Min	(3x50)x24Ah	PX50ms/c/40/0 + BX50ms/u/5b +BX50ms/u/5a	(2x580+550)x1800x750	2040
Options					
BX50ms/u/0	Batterie-Leergehäuse	—		580x1800x750	130
BX50ms/u/A	Batteriekabinett	40x24 Ah	BX50ms/u/A	580x1800x750	550
BX50ms/u/B	Batteriekabinett	2 x (40x24) Ah	BX50ms/u/B	580x1800x750	910
BX50ms/u/C	Batteriekabinett	3x (40x24 Ah)	BX50ms/u/C	580x1800x750	1270
BX50ms/u/5a	Batteriekabinett	50x24 Ah	BX50ms/u/5a	580x1800x750	640
BX50ms/u/5b	Batteriekabinett	2 x (50x24 Ah)	BX50ms/u/5b	580x1800x750	1090